



ARTEX C406-2 Series

406 MHz Emergency Locator Transmitters

(Type AF ELT) Cospas/Sarsat Approved,
FAA TSO C126 Approved, JTSO-2C126 Approved

The Artex **C406-2** transmits on all 3 emergency frequencies (121.5/243.0 and 406 MHz). The ELT automatically activates during a crash and transmits the standard swept tone on 121.5 and 243.0 MHz. Every 50 seconds for 520 milliseconds (long message protocol) the 406.025 MHz transmitter turns on and transmits an encoded digital message to the Cospas/Sarsat satellite system. The ELT can be programmed with the aircraft's 24-bit address as well as latitude/longitude information from the aircraft navigation system when used with the Artex ELT/NAV Interface (P/N 453-6500). Also available is the Artex **C406-2HM**, which is equipped with a 6 axis "G" Switch for helicopter installations. The mounting hardware for the **C406-2** Series is compatible with all previous versions of Artex 406 MHz ELT's.

SPECIFICATIONS:

Operating Frequencies:

406.025 MHz \pm 2 kHz Biphase L (16K0G1D)
121.5 & 243.0 MHz \pm 0.005% (A3X)

Output Power:

406 MHz: 5 W \pm 2 dB (520 ms / 50 sec)
for 24 hours @ -20° C
121.5/243.0 MHz: 100 mW min (+20 dBm)
for 50 hours @ -20° C)

Output connector:

BNC Female

Activation:

Automatic by 4.5 ft/sec G-Switch or Manual

Battery:

5 year Lithium (LiMnO₂, solid cathode)

Temperature

Operating: -20° C to +55° C
Storage: -55° C to +85° C

Self Test:

G-Switch enabled
406 MHz Power
Antenna/Coax Connection
Position Data Present
Low Battery

Remote Control:

ON/OFF/RESET

Antenna:

Rod (110-320) (<350 KTS)
Blade (110-337) (Mach 1)

Mounting Hardware:

Mounting Tray 452-5050
Protective Top Cover P/N 452-3052
End Cap P/N 452-5052

Other Parts:

Coax cables
Buzzer (to alert ground crews of accidental activation)

Weights:

ELT Transmitter: 3 LB 5.8 oz Max (1.53 Kg)
Mounting Tray: 7 oz (200 g)
Protective Top Cover: 6.7 oz (190 g)
End Cap: 3.8 oz (108 g)
Total Weight: 2.02 Kg

Measurements:

ELT Transmitter with Mounting Hardware Installed:
11.74" (298mm) L x 3.90" (99mm) H x 3.82" (97mm) W

Part Numbers:

C406-2: 453-5000 (Transmitter Only)
C406-2HM: 453-5001 (Transmitter Only)

Artex reserves the right to alter or modify any of the above specifications



C406-2 System

